Panasonic

MODEL NO. **KX-T7030**Operating Instructions

Making Calls			
Press the SP-PHONE button or lift the handset first.			
Feature		Operation	
Inter Office Calling	Station to station dialing within the system.	extension number or DSS	
Individual Line Access	Any CO line can be directly selected.	phone number	
Automatic Line Access	An idle CO line will be automatically selected.	9 phone number	
System Speed Dialing	Any extension users can make an outside call with a simple operation.	access code	
One-Touch Dialing	A system feature or a telephone number can be activated with simply pressing the Programmable Feature button programmed in advance.	Programming: Set the memory switch to "PROGRAM". F one-touch code phone number STORE Replace the memory switch to the "SET".	
	When a L	ine is Busy	
Automatic Call Back Busy (Camp-on)	This feature automatically notifies you when the busy CO line or extension becomes free.	Outside Calls: CO Hear a busy tone Intercom Calls: Extension number Hear a busy tone Hear a busy tone Hear a busy tone	
Redial	The last dialed number will be redialed at one touch. • Automatic redial can work in upgraded systems.	SP-PHONE or Lift the handset	

	Receiv	ing Calls
Feature		Operation
Answer	Answering the incoming calls.	SP-PHONE or Lift the handset
Automatic Answer— Intercom	The extension user can answer an intercom call in the automatic hands-free mode.	Setting: The indicator lights in red.
		Canceling: Auto Answer The indicator goes out.
Dial Call Pickup	An extension user can answer any ringing extension within their own extension group.	The pickup code depends on the EMSS Control Unit.
The programme of	While Having	a Conversation
Hold— CO Line	An outside call will be put on hold during a conversation.	The CO line indicator flashes in green. Other extensions flash in red.
		Retrieving: The indicator lights in green.
		Retrieving from another extension: CO The indicator lights in green.
Hold— Intercom	An intercom call will be put on hold during a conversation.	The intercom indicator flashes in green.
		Retrieving: INTERCOM The indicator lights in green.
Call Transfer to Extension	An outside call or an intercom call will be transferred to any extension.	Transferring after the other extension answers: Wait for an answer and announce Hang up
		Transferring without announcing to the other extension:
		TRANSFER extension number Hang up

For further details, please refer to the Electronic Modular Switching System (EMSS) Control Unit Manual.

System Features	Operation	

Please use this Operating Instructions for basic operations, and for other features, please refer to the Electronic Modular Switching System (EMSS) Control Unit Manual.

Notice

A series of the beep tone may sound periodically when the MEMORY switch is set to the "PROGRAM". This is a normal condition.

Matsushita Electric Industrial Co., Ltd.

Central P.O. Box 288, Osaka 530-91, Japan